

# FM/IV PC-controlled Congress Voting System

## FM/IV-01V Chairman unit with Voting Keys



### Technical Data

· Power supply	DC24V Current 20mA
· Maximum power consumption	1.4W
· Output recording power	less than 1V imbalance output
· Microphone	Condenser
· Polar	Cardioid
· Frequency response	50Hz 12.5KHz
· Sensitivity	-43dB±3
· Impedance	Low
· Length	48cm
· Material of gooseneck	Black chromium-plated
· Weight	220g
Case	
· Weight	Approx. 750g
· Color & case material	Deep grey ABS case
· Cable	8 core
· Working temperature	0°C- 40°C

### Configuration

- Flexible gooseneck mic (2 segments)
- Canon socket for mic plug-in
- Red LED ring at gooseneck head
- Dual loudspeaker
- Red priority button (in chairman unit)
- Green Speaking ON/OFF button
- LED indicator to show mic is ON
- Five Voting Keys (++,+,0,-,--)
- Each voting key had a LED lamp
- 2m connection cable
- 15pin D-sub connector

