

FM/V Digital Congress Voting System

FM/V-07 Chairman unit with Voting Keys with LCD Display



Technical Data

· Internal speaker	8 Ω , 2V
· Power supply	DC24V Current 20mA
· Maximum power consumption	1.4W
· Output recording power	less then 1V imbalance output
· Microphone	Condenser
· Polar	Cardioid
· Frequency response	50Hz 12.5KHz
· Sensitivity	-43dB \pm 3
· Impedence	Low
· Length	40cm
· Material of gooseneck	Black chromium-plated
· Weight	220g
Case	
· Weight	Approx. 750g
· Color & case material	Deep grey ABS case
· Cable	8 core
· Working temperature	0°C- 40°C

Configuration

- Flexible gooseneck mic
- 4 pin screw-in socket for gooseneck mic
- Red LED ring at gooseneck head
- Internal loudspeaker
- Speaking (MIC) ON/OFF key
- Earphone jack, 3.5mm
- Card reader with LED indicator
- 5 Voting keys (++,+,0,-,-)
- 128 x 64 LCD display
- Warning lamp on rear side x 2
- 2m detachable cable (1.65m + 0.35m)
- 15pin D-sub connector

