

## RX106 Infrared Receiver



### Technical Data

- Power consumption 36mW maximum
- Number of channels 6 or 12 channels
- Receiving frequency 55KHz-535KHz with 40KHz channel spacing (except 455KHz)
- Intermediate frequency 455KHz
- Modulation FM
- Frequency response 125-8000Hz
- Weight 106g without battery
- Color & case material Deep grey ABS case
- Battery type AAA battery x 2
- Battery Life Approx. 120hrs

### Configuration

- Indicator Operation LED x 1
- Focusing device Optical lens x 1
- Control Channel selector x 1  
Volume selector x 1
- Headphone socket 3.5mm jack female socket